

bq241x0/3/4/5/8/9, bq24170/1/2, bq24133, bq24610/6, and bq24630/40/50 Comparison

Tahar Allag and Wang Li

Battery Power Applications

ABSTRACT

This application report provides a comparison among bq241x0/3/4/5/8/9, bq24170/1/2, bq24133, and bq246xx. The document presents the main differences and describes the main features of each part. It assists designers in selecting the most suitable charger for their application.

1 Summary Table of bq241x0/3/4/5/8/9, bq24170/1/2, bq24133, and bq246xx Comparison

Table 1 compares different parameters of the bq241x0/3/4/5/8/9, bq24170/1/2, bq24133, and bq246xx. It provides the input voltage range, the maximum charging current during the fast-charge phase of each charger, the power path, the availability of the Dynamic Power Management function, temperature qualification range, and the packaging type and size.

Table 1. Summary of Comparison Table

Device	Vin (OVP)	Fast-Charge Current	V-charge	Power-Path Gate Drive	DPM IIN	Switching MOSFET	Frequency	Battery	Temperature Qualification Profile	Package
bq241x0/3/4/8/9	4.3-16 V (N/A)	Max 2 A	1-3 Cell 4.2 V/cell	N/A	N/A	Internal	1.1 MHz	Li-ion or Li-polymer	0°-45°C or wider	3.5x4.5 QFN-20
bq24105/15/25	4.3-16 V (N/A)	Max 2 A	1-3 Cell Adjustable	N/A	N/A	Internal	1.1 MHz	Li-ion or Li-polymer	0°-45°C or wider	3.5x4.5 QFN-20
bq24170	4.5-17 V (OVPSET)	Max 4 A	1-3 Cell 4.2 V/cell	ACFET NMOS BATFET PMOS	Yes	Internal	1.6 MHz	Li-ion or Li-polymer	0°-40°C or wider	3.5x5.5 QFN-24
bq24171	4.5-17 V (OVPSET)	Max 4 A	1-3 Cell Adjustable	ACFET NMOS BATFET PMOS	Yes	Internal	1.6 MHz	Li-ion or Li-polymer	JEITA	3.5x5.5 QFN-24
bq24172	4.5-17 V (OVPSET)	Max 4 A	1-3 Cell Adjustable	ACFET NMOS BATFET PMOS	Yes	Internal	1.6 MHz	Li-ion or Li-polymer	0°-40°C or wider	3.5x5.5 QFN-24
bq24133	4.5-17 V (OVPSET)	Max 2.5 A	1-3 Cell 4.2 V/cell	ACFET:NMOS BATFET:PMOS	Yes	Internal	1.6 MHz	Li-ion or Li-polymer	0°-40°C or wider	3.5x5.5 QFN-24
bq24610	5-28 V (32 V)	Max 10 A (10 mΩ Rsns)	1-6 Cell Adjustable	ACFET PMOS BATFET PMOS	Yes	External	600 kHz	Li-ion or Li-polymer	0°-40°C or wider	4x4 QFN-24
bq24616	5-28 V (32 V)	Max 10 A (10 mΩ Rsns)	1-6 Cell Adjustable	ACFET PMOS BATFET PMOS	Yes	External	600 kHz	Li-ion or Li-polymer	JEITA	4x4 QFN-24
bq24630	5-28V (32 V)	Max 10 A (10 mΩ Rsns)	1-7 Cell Adjustable	ACFET PMOS BATFET PMOS	Yes	External	300 kHz	LiFePO4	LiFePO4	4x4 QFN-24
bq24640	5-28 V (32 V)	Max 10 A (10 mΩ Rsns)	2.1~26 V	N/A	No	External	600 kHz	Super capacitor	0°-40°C or wider	3.5x3.5 QFN-16
bq24650	5-28 V (32 V)	Max 4 A (10 mΩ Rsns)	1-6 Cell Adjustable	N/A	Input voltage (Vin) DPM	External	600 kHz	Li-ion or Li-polymer	0°-40°C or wider	3.5x3.5 QFN-16

bqSWITCHER is a trademark of Texas Instruments.

2 bq241x0/3/4/8/9

The bq241x0/3/4/8/9 series are highly integrated charge management devices for single-, two-, or three-, 4.2-V cells of Li-ion and Li-polymer batteries. They have integrated power FETs capable of a charging rate up to 2 A with high-accuracy voltage and current regulation. This part is featured with charge status outputs STAT1 and STAT2 to indicate varied charge operation conditions, charge enable (CE) pin to disable or enable the charging process, open-drain power good (PG) to indicate the presence of the ac-to-dc adapter, sleep mode for low-power consumption if the Vcc pin is removed from the circuit, and an output overvoltage protection to protect the device from high voltages of the battery terminals.

This device family charges the battery in three phases: precharge (conditioning), constant-current regulation phase, and constant-voltage regulation phase. Based on the current level, the charger terminates the charging process for any currents below the selected threshold current level.

During the precharge phase, the charging current is regulated to low levels to revive the undercharged cell of the battery. In the current-regulation phase, the current is kept constant and relatively higher than the previous phase to allow a fast-charging time. As the battery voltage reaches the regulation level, the charger maintains the battery voltage regulated at constant level until the current drops below the termination level.

3 bq241x5

The bq241x5 is a bqSWITCHER™ series that are highly integrated Li-ion and Li-polymer chargers. The bq24105 also can be used to charge LiFePO₄ battery chemistry. The bq241x5 is different than bq241x0/3/4/8/9 series in that it charges 1-to-3 cells with adjustable output voltage instead. The charging phases and other features are similar to the ones described in the previous device family.

4 bq24170/2

These charger series are highly integrated, stand-alone, Li-ion and Li-polymer chargers. They can be used for 1-to-3 cells with charging current of up to 4 A. The battery charge voltage is fixed to 4.2 V/cell for the bq24170 and adjustable for the bq24172. The input operating voltage range is from 4.5 V to 18 V with 30-V input rating featured with adjustable overvoltage protection. They can operate at up to 94% efficiency with automatic power-path selection between the adapter and the battery.

The bq24170/2 charges the battery in three phases, the precharge phase, the fast-charge current phase, and the fast-charge voltage phase. During the precharge current-regulation phase, the battery is charged with constant current equal to 10% of the fast-charge current regulation. This phase allows a safe revival of the deeply discharged cells. After the cell's voltage increases above the threshold voltage level, the charging current goes to 100% to allow fast-charging rate. After reaching the regulation voltage, the charger maintains the cell's voltage constant without regulating the current. As the charging current drops below 10% of the full charging level, the termination occurs and the charger stops injecting current into the battery.

5 bq24171

The bq24171 is also a highly integrated, stand-alone, Li-ion and Li-polymer, switch-mode battery charger. Its input operating voltage is from 4.5 V to 17 V and capable of charging 1-to-3 cells with a fixed output voltage of 4.2 V per cell with fast-charge current of up to 4 A. This charger is featured with JEITA-compatible battery temperature sensing. It monitors the battery temperature by controlling the charge rate at lower temperature and lower charge voltage at high temperature. It is included with a Dynamic Power Management to decrease or increase the charging current with respect to the system demands and the input current limits. The bq24171 also charges the battery in the phases as described in the bq24170/2 section.

6 bq24133

The bq24133 is also a highly integrated, stand-alone charger for Li-ion and Li-polymer chemistries. It is integrated with two N-channel power MOSFETs. As in the previous sections, this charger has three phases: the preconditioning, the constant-current, and the constant-voltage regulation. It features Dynamic Power Management to control the charge current with the limits of the input power and the demanding system power. The allowed input voltage for this part is up to 20 V and has a fixed output voltage of 4.2 V with a maximum charging current of 2.5 A.

7 bq24616

The bq24616 is a JEITA (Japan Electronic Information Technology Association) guideline-compatible, stand-alone, synchronous, switch-mode battery charger for Li-ion and Li-polymer battery chemistries. The charger continuously monitors the battery temperature by measuring the battery temperature and controls both the charge voltage and charge current. Also the part is featured with the Dynamic Power Management (DPM) to reduce the battery charge current as the input current reaches its limits. The allowed input voltage range for this part is from 5 V to 28 V and the output is adjustable for 1-to-6 cells with a maximum charging current of 10 A. The switching MOSFETs are externally implemented in this part.

8 bq24610

The bq24610 is an integrated Li-ion and Li-polymer charger. It charges batteries in three phases as described in the bq24170. It supports 1-to-6 battery cells from 5-V to 28-V input voltage with adjustable charge voltage. The charging current can go up to 10 A. The switching MOSFETs are externally implemented. This part features a low-input, quiescent current of less than 1.5 mA at off-state and low, battery-discharge current of less than 15 μ A at off-state

9 bq24630

This device is a switch-mode, battery charge controller designed specifically for a lithium phosphate battery. The bq24630 controls external switches to prevent battery discharge back to the input, to connect the adapter to the system, and to connect the battery to the system using 6-V gate drives for better system efficiency. It features DPM. These features reduce battery charge current when the input power limit is reached to avoid overloading the ac adapter when supplying the load and the battery charger simultaneously. A highly accurate current-sense amplifier enables precise measurement of input current from the ac adapter to monitor the overall system power.

10 bq24640

The bq24650 is a highly integrated, switch-mode, super-capacitor charger. Its input voltage can vary from 5 V to 28 V. This device charges super capacitors in two phases based on the state of charge of the battery at any given time as shown in [Table 1](#). The first phase is the constant-current mode. The charger in this mode can start charging the super capacitor from 26 V down to 0 V at constant current set by the ISET pin. The second phase is the constant-voltage mode where the charging voltage is set using a resistor divider from the output to the ground.

11 bq24650

The bq24650 is an integrated, switch-mode, battery-charge controller that supports input voltage from 5 V to 28 V and battery voltage from 2.1 V to 26 V. The charging current can be adjusted using a sense resistor. It offers a constant-frequency, synchronous, PWM controller with high-accuracy current and voltage regulation.

12 References

1. bq241xx, *Synchronous Switchmode, Li-Ion and Li-Polymer Charge-Management IC With Integrated Power FETs (bqSWITCHER™)* data sheet ([SLUS606](#))
2. bq24171, *JEITA Compliant Stand-Alone Switch-Mode Li-Ion and Li-Polymer Battery Charger With Integrated MOSFETs and Power Path Selector* data sheet ([SLUSAF2](#))

3. bq24170/2, 1.6-MHz Synchronous Switch-Mode Li-Ion and Li-Polymer Stand-Alone Battery Charger With Integrated MOSFETs and Power Path Selector data sheet ([SLUSAD2](#))
4. bq24133, 1.6-MHz Synchronous Switch-Mode Li-Ion and Li-Polymer Stand-Alone Battery Charger with Integrated MOSFETs and Power Path Selector data sheet ([SLUSAF7](#))
5. bq24616, JEITA Guideline Compatible Stand-Alone Synchronous Switch-Mode Li-Ion or Li-Polymer Battery Charger with System Power Selector and Low Iq data sheet ([SLUSA49](#))
6. bq24617, Stand-Alone Synchronous Switch-Mode Li-Ion or Li-Polymer Battery Charger with System Power Selector and Low Iq data sheet ([SLUS892](#))
7. bq24618, Stand-Alone USB-Friendly Synchronous Switch-Mode Li-Ion or Li-Polymer Battery Charger with System Power Selector and Low Iq data sheet ([SLUSA55](#))

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Mobile Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Transportation and Automotive	www.ti.com/automotive
Video and Imaging	www.ti.com/video

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated